T40 selection & technical guide

T40 Track Busway READY Retractable Cord Reel

Download a configuration sheet before selecting ordering options. Match the voltage, output type, quantity and protection to the required build.

120V | 20A | One 5-20C inline connector

One-page cut sheet (PDF) **Wiring details (PDF)**

120V | 20A | One duplex 5-20R receptacle (2 outlets)

One-page cut sheet (PDF) **Wiring details (PDF)**

120V | 20A | Two duplexes (4 x 5-20R outlets)

One-page cut sheet (PDF) **Wiring details (PDF)**

120V | 20A | One GFCI duplex 5-20R receptacle

One-page cut sheet (PDF) **Wiring details (PDF)**

120V | 20A | Two GFCI duplexes (4 x 5-20R outlets)

One-page cut sheet (PDF) **Wiring details (PDF)**

Existing catalogue numbers

T40 Track Busway READY Retractable Cord Reel

MD40-2-120-CB20-CR-45-520C-G | Single 5-20C

MD40-2-120-CB20-CR-45-520D-G | Duplex 5-20R

MD40-2-120-CB20-CR-45-520Q-G | Quad 5-20R

MD40-2-120-CB20-CR-45-520D-G-GFCI | Duplex 5-20R with GFCI

MD40-2-120-CB20-CR-45-520Q-G-GFCI | Quad 5-20R with GFCI

Connection and construction

T40 Track Busway READY Retractable Cord Reel

Catalogue numbers and variant identities are retained. C identifies a female cord connector; R identifies a mounted receptacle. Existing ST/DT/SB/DS/Q codes remain valid.

PowerDrop cord-end boxes are used for duplex and quad straight-blade outputs. Other outputs use inline female connectors. Match the output count to the individual sheet.

120V standard fittings select lower-deck A or B. Where offered, the -WP tap-off ships with its C-phase whip installed and wired at the factory. Standard double drops use A+B. A -WP double drop supplies one cord from C and one from A or B.

208V two-pole builds use standard A+B or factory -WP for A+C or B+C. 240V two-pole builds use A+B. Three-phase assemblies take lower-deck A+B and upper-deck C through the factory-installed and wired whip.

The 40A busway rating does not replace the branch/device rating. Follow the selected sheet and marked-unit ratings. Unbreakered assemblies require appropriately rated upstream protection.

No enclosure dimensions are inferred from photographs. Project-specific top-mounted/bottom-fed whip arrangements are distinct from standard C-phase access.

45 ft reels: all outlets share the documented 20A branch. Support rods must exceed 1/4 in. nominal diameter; 1/4-20 rod is not permitted.

T40 installation instructions (PDF)